

ELD2 series DC Servo Drive

ELD2 low-voltage DC servo is a special motion control product designed for machines and applications that request a best balance between outstanding and reasonable cost.

Combined with abundant features like MFC, vibration suppression, multi-mode filter function etc. It provide machines a compact size, low tuning works.

Feature:

- ◆ Power range up to 2.5kW
- ◆ Current range up to 180Amp
- ◆ Easy tuning
- ◆ Simple, flexible to control
- ◆ Modbus RTU / CANopen
- ◆ PR-Mode
- ◆ Notch filter, damping filter
- ◆ 1000line / 2500line incremental encoder / 17bit Serial signal encoder



Technical Specification

Power & Environment					
Drive model		ELD2-RS7005 ELD2-CAN7005	ELD2-RS7010 ELD2-CAN7010B	ELD2-RS7015B ELD2-CAN7015B	ELD2-RS7020B ELD2-CAN7020B
Size(mm)		118*79.5*25.5(RS) 140*79.5*25.5(CAN)	118*79.5*25.5(RS) 140*79.5*25.5(CAN)	175*101.5*33	175*101.5*33
Rated power(kW)		0.1	0.4	0.6	0.75
Rated output current(Arms)		5	10	15	20
Max output current(Apeak)		21.2	35 (RS) 42.5 (CAN)	45	80
Main power	Voltage(V)	DC24V-70			
	Current(A)	5Arms ($\leq 48Vdc$) 3.5Arms ($> 48Vdc$)	10Arms ($\leq 48Vdc$) 7Arms ($> 48Vdc$)	15Arms ($\leq 48Vdc$) 11Arms ($> 48Vdc$)	20Arms ($\leq 48Vdc$) 14Arms ($> 48Vdc$)
Auxiliary power	Voltage(V)	——			
Control power	Voltage(V)	DC12-24			
	Current(mA)	≥ 12			
Control method		IGBT PWM sinusoidal Wave Drive			
Overload		300%			
Brake resistor		External connection			
Safe function		——			
Protection rank		IP20			

Datasheet of ELD2 Series Drive

Power & Environment				
Drive model		ELD2-RS7030B ELD2-CAN7030B	ELD2-RS7040B ELD2-CAN7040B	ELD2-RS7060B ELD2-CAN7060B
Size(mm)		175*101.5*33	194*103*41	194*103*41
Rated power(kW)		1.2	1.5	2.5
Rated output current(Arms)		30	40	60
Max output current(Apeak)		90	120	180
Main power	Voltage(V)	DC24V-70		
	Current(A)	30Arms (≤48Vdc) 21Arms (>48Vdc)	40Arms(≤48Vdc) 28Arms (>48Vdc)	60Arms(≤48Vdc) 42Arms (>48Vdc)
Auxiliary power	Voltage(V)	——	DC24V-70	
Control power	Voltage(V)	DC12-24		
	Current(mA)	≥12		
Control method		IGBT PWM sinusoidal Wave Drive		
Overload		300%		
Brake resistor		External connection		
Safe function		——	STO	
Protection rank		IP20		

Communication & Connection		
Type	ELD2-RS***	ELD2-CAN***
Pulse input	2 fast pulse input, 5V only	——
Analog input	1 analog input: -10V to +10V	——
Digital input/output	4programmable OC inputs, 24V 2 programmable OC outputs, 24V	
Communication interface	RS485	CAN
Feedback Supported	1000, 2500lines incremental TTL encoder and Serial signal encoder	

Matched Motors	
Power Range	Up to 2.5kw
Voltage Range	24 - 70Vdc
Encoder Type	1000-Line, 2500 -Line, 17-Bit
Motor Size	40mm,42mm,57mm,60mm,80mm frame or other size
Other Requirements	Brake. oil-seal. protection level. Shaft & connector can be customized

Operating Environment

Servo Drive, Servo Motor Storage Circumstance Requirement

Item	ELD2 series drive
Temperature	-20-80℃
Humidity	Under 90%RH (free from condensation)
Atmospheric environment	Indoor(no exposure)no corrosive gas or flammable gas, no oil or dust
Altitude	Lower than 1000m
Protection level	IP20(no protection)


Datasheet of ELD2 Series Drive

Servo Drive, Servo Motor Installation Circumstance Requirement


Item	ELD2 series drive
Temperature	0-55℃
Humidity	Under 90%RH(free from condensation)
Atmospheric environment	Indoor(no exposure)no corrosive gas or flammable gas, no oil or dust
Altitude	Lower than 1000m
Protection level	IP00(no protection)

Model


ELD2-RS7005/ELD2-RS7010




ELD2-CAN7005B/ELD2-CAN7010B



ELD2-**7015B/ELD2-**7020B/ELD2-**7030B




ELD2-**7040B/ELD2-**7060B



Connectors and Pin Assignment

Power terminal

Power terminal	Pin	Signal	Input / Output	Details
	1	VCC	Input	Power supply input
	2	GND	Input	Ground connection
	3	U	Output	Motor phase U
	4	V	Output	Motor phase V
	5	W	Output	Motor phase W
	6	PE	Output	Motor protective connection

Regenerative resistor

RBR		Pin	Signal	Input / Output	Details
RBR		1	RBR+	Output	Regenerative resistor +
		2	RBR-	Output	Regenerative resistor -


Signal Explanation of Control Signal Port-CN1

CN1		Pin	Signal	IO	Detail		
CN1							


Datasheet of ELD2 Series Drive

		18	DO1	Output	Digital output signal 1 , (ALARM) , 24V, 8mA
		19	DO2	Output	Digital output signal 2 , (Servo-Ready) , 24V, 8mA
		20	COM_O	Output	Digital output signal commonality ground, 24V


Encoder Input Port

CN2		Pin	Signal	IO	Detail
CN2		1	SHIELD	Input	Ground terminal for shielded
		2	HU	Input	Hall sensor U input
		3	HW	Input	Hall sensor W input
		4	HV	Input	Hall sensor V input
		5	VCC	Input	+5V for encoder power supply
		6	GND	Input	
		7	EZ+/D+	Input	Encoder channel Z+ put/ Serial encoder signal
		8	EZ-/D-	Input	Encoder channel Z- input/ Serial encoder signal
		9	EB+	Input	Encoder channel B+ input
		10	EB-	Input	Encoder channel B- input
		11	EA+	PE	Encoder channel A+ input
		12	EA-	Input	Encoder channel A- input


Communication port

CN7		Pin	Detail
RS232		1	5V
		2	TX
		3	GND
		4	RX

Bus connector- IN or OUT

BUS		Pin	Modbus(RS485)	CANopen
CANopen / Modbus(RS485)		1	485data+	CANH
		3	485 data-	CANL
		5	GND	GND
		other	NC	NC

STO connector


STO		Pin	Detail
STO		1	GND
		2	5V
		3	STO 1-
		4	STO 1+
		5	STO 2-
		6	STO 2+
		7	EDM-
		8	EDM+

Datasheet of ELD2 Series Drive

Auxiliary power

Auxiliary power		Pin	Detail
Auxiliary power		1	VCC+
		2	GND

Rotary Code Switch—Modbus(RS485) / CANopen

RCS		NO.	Slave ID	NO.	Slave ID
S1		0	Modbus : Default Pr5.31=16 CANopen: Default Pr0.23=16	8	8
		1	1	9	9
		2	2	A	10
		3	3	B	11
		4	4	C	12
		5	5	D	13
		6	6	E	14
		7	7	F	15

Dip Switch

Switch		Pin	Detail			
SW	SW4 SW3 SW2 SW1 OFF ON	SW1	Modbus / CANopen baud rate:			
			SW1	SW2	Modbus Baud rate	CANopen Baud rate
		off	off	Default Pr5.30=9600	Default Pr0.24=1M	
		SW2	on	off	19200	500K
			off	on	38400	250K
			on	on	57600	125K
		SW3	Bus terminal resistance: ON: 120ohm OFF: Null			
		SW4	Parameter	ELD2-RS****	SW4	Detail
			Pr6.33=0	Rotation direction	off	CCW
					on	CW
			Pr6.33=8	Modbus slave ID MSB	off	0: Slave ID = RCS
					on	1: Slave ID = 16 + RCS
Parameter	ELD2-CAN****		SW4	Detail		
---	CANopen slave ID MSB		off	0: Slave ID = RCS		
			on	1: Slave ID = 16 + RCS		